



ANSI DIMS. DESIGN.	PUMP SIZE	CP	D	2E ₁	2E ₂	F	DIA. H	O	DIA. U	KEYWAY	V MIN.	X	Y
AA	1-1/2 x 1 x 6	17-1/2	5-1/4	6	0	7-1/4	5/8	11-3/4	7/8	3/16 x 3/32	2	6-1/2	4
AB	3 x 1-1/2 x 6	17-1/2	5-1/4	6	0	7-1/4	5/8	11-3/4	7/8	3/16 x 3/32	2	6-1/2	4
AA	1-1/2 x 1 x 8	17-1/2	5-1/4	6	0	7-1/4	5/8	11-3/4	7/8	3/16 x 3/32	2	6-1/2	4
A60	3 x 2 x 8	23-1/2	8-1/4	9-3/4	7-1/4	12-1/2	5/8	17-3/4	1-1/8	1/4 x 1/8	2-5/8	9-1/2	4
A70	4 x 3 x 8G	23-1/2	8-1/4	9-3/4	7-1/4	12-1/2	5/8	19-1/4	1-1/8	1/4 x 1/8	2-5/8	11	4
A60	3 x 2 x 10	23-1/2	8-1/4	9-3/4	7-1/4	12-1/2	5/8	17-3/4	1-1/8	1/4 x 1/8	2-5/8	9-1/2	4
A70	4 x 3 x 10H	23-1/2	8-1/4	9-3/4	7-1/4	12-1/2	5/8	19-1/4	1-1/8	1/4 x 1/8	2-5/8	11	4